

ALL STATIONS THIS NET ALL STATIONS THIS NET THIS IS [callsign]
NET CONTROL FOR THE VHF SIMPLEX EXERCISE

THIS IS A DIRECTED NET WAIT

STATIONS CHECKING INTO THE NET SLOWLY SAY "THIS IS" RELEASE
YOUR PTT THEN SAY YOUR CALLSIGN

THIS IS [callsign] ANY STATION FOR THE NET YOUR CALLSIGN OVER

[record stations]

[acknowledge stations]

THIS IS [callsign] ROGER OUT

THIS IS [callsign] ADDITIONAL STATIONS YOUR CALLSIGN OVER

[record stations]

[acknowledge stations]

THIS IS [callsign] ROGER ANSWER AFTER [station] OUT

THIS IS [callsign] ANY STATION ASKED TO BE ALTERNATE NET
CONTROL SAY YOUR CALLSIGN AND ASK FOR ADDITIONAL STATIONS
WAIT

EXAMPLE FOLLOWS

THIS IS W4XYZ FOR NET CONTROL ADDITIONAL STATIONS OVER
END OF EXAMPLE OUT

THIS IS [callsign] ALL STATIONS BE AWARE THERE WILL BE PERIODS
OF TIME YOU ARE ASKED TO WAIT OR STANDBY

I SAY AGAIN THERE WILL BE PERIODS OF TIME YOU ARE ASKED TO WAIT OR STANDBY OUT

THIS IS [callsign] ARE THERE ANY QUESTIONS BEFORE WE PROCEED YOUR CALLSIGN OVER

[acknowledge station's question with response]

[ask for further questions and if none say NOTHING HEARD OUT]

THIS IS [callsign] ALL STATIONS QSY TO [frequency] I SAY AGAIN QSY TO [frequency] AND WAIT FOR NET CONTROL TO CALL THE ROSTER AND FURTHER DIRECTIONS OUT

[QSY to assigned frequency]

THIS IS [callsign] FOR NET CONTROL ON [frequency] WAIT OUT

THIS IS [callsign] STANDBY FOR THE ROSTER WAIT

THIS IS [callsign] WHEN YOU HEAR YOUR CALLSIGN, RESPOND BY SAYING YOUR CALLSIGN AND PROVIDE A SIGNAL REPORT WAIT

[call roster, ask for signal report, record response]

THIS IS [callsign] ROGER OUT

THIS IS [callsign] ADDITIONAL STATIONS YOUR CALLSIGN OVER

[record stations]

[acknowledge stations]

THIS IS [callsign] ARE THERE ANY RELAYS OVER

[record stations]

[acknowledge stations]

THIS IS [callsign] ROGER ANSWER AFTER [station] OUT

[station] THIS IS [callsign] ACT AS ALTERNATE NET CONTROL AND
MAKE A CALL FOR ADDITIONAL STATIONS OUT

[record stations]

[acknowledge stations]

THIS IS [callsign] COPY BY INTERCEPT OUT

THIS IS [callsign] ALL STATIONS QSY TO [frequency] I SAY AGAIN
ALL STATIONS QSY TO [frequency] OUT

THIS IS [callsign] COMMENTS FOR THE NET YOUR CALLSIGN OVER

[record station and comments]

THIS IS [callsign] THANK YOU FOR YOUR TIME AND COOPERATION

THIS CONCLUDES THE FIRST VHF SIMPLEX EXERCISE 73 OUT